

# How to configure port forwarding?

It is suitable for: **N150RA, N300R Plus, N300RA, N300RB, N300RG, N301RA, N302R Plus, N303RB, N303RBU, N303RT Plus, N500RD, N500RDG, N505RDU, N600RD, A1004, A2004NS, A5004NS, A6004NS**

## Application:

AP Client mode allows users with laptop to surf Internet by wireless connection. It's designed to add wireless function for existed wired Router.

## STEP-1: Connect your computer to the router

1-1. Connect your computer to the router by cable or wireless, then login the router by entering http://192.168.1.1 into the address bar of your browser.




Note: The default IP address of TOTOLINK router is 192.168.1.1, the default Subnet Mask is 255.255.255.0. If you can't log in, Please restore factory settings.

1-2. Please click Setup Tool icon  to enter the router's setting interface.



1-3. Please login to the Web Setup interface (the default user name and password is admin).




## STEP-2:

Click **Advanced Setup->Wireless->Wireless Mutibridge** on the navigation bar on the left.



## STEP-3:

Finished the settings on the page as below, Click Add button after setting.



- **Operation:** Start
- **Wireless Mode:** Use Wireless WAN
- **SSID:** Scan the router' AP
- **Authentication & Encryption:** choose encryption type and enter the password.

## STEP-4:

After click Search AP, it will pop up the page. Choose the AP by double click and then click Select AP button.




## STEP-5:

Click **Advanced Setup->Network->LAN/DHCP Server** on the navigation bar on the left.



## STEP-6:

Change the third column of the LAN IP (**LAN segment should not be the same with the primary router**). Generally, enter 2 if there's no particular requirement. Then click Apply& Restart button.



## STEP-7:

Wait for 40 seconds, and then it will pop up a window prompts you to reconnect the website as the LAN IP has changed.



## STEP-8:

Login the router's setting interface, and check the Internet status.

