

N600R MAC filter settings

It is suitable for : **N600R, A800R, A810R, A3100R, T10, A950RG, A3000RU**

Application introduction:

Solution about how to configure Wireless MAC Filtering on TOTOLINK router.

STEP-1:

Connect your computer to the router by cable or wireless, then login the router by entering http://192.168.0.1 into the address bar of your browser.

←

→

↺

🏠

🔍

192.168.0.1

→

Note:

The default access address varies depending on the actual situation. Please find it on the bottom label of the product.

STEP-2:

User Name and Password are required, by default both are **admin** in lowercase letter. Click **LOGIN**.

USER LOGIN

Forget Password?

User Name

admin

Password

•••••

LOGIN

STEP-3:

Please go to **Firewall ->MAC Filtering** page, and check which you have selected.Select **Enable**, then Input your own **MAC Address** which you want to restrict or click **Scan** bottom to restrict it and give a **Comment** for this item, then Click **Add**.

TOTO LINK

The Smartest Network Device

N600R (Firmware V5.3c.3243)

System Status

Operation Mode

Network

Wireless

QoS

Firewall

Firewall Type

IP/Port Filtering

MAC Filtering

URL Filtering

Port Forwarding

VPN Passthrough

DMZ Setting

Rule Schedule Setting

Management

MAC Filtering

Entries in this table are used to restrict certain types of data packets from your local network to Internet through the Gateway. Use of such filters can be helpful in securing or restricting your local network. When [Enable] is selected, if the firwall type is [Black List], entries in this table are used to restrict certain types of data packets from your local network to Internet through the Gateway. If the firwall type is [White List], entries in this table are used to allow data packets from your local network to Internet through the Gateway.Use of such filters can be helpful in securing or restricting your local network. When [Disable] is selected, All entries in this table do not take effect.

On/Off

Enable

Add a rule

MAC Address

Scan

Comment

Add

Current MAC Filtering List (The maximum entry count is 10)

ID	MAC Address	Comment	Select
----	-------------	---------	--------

Delete

Reset

Note:You need add items in this way one by one.